

# DENON AVR control protocol

Ver 6.4.0

Application model : AVR-3310/AVR-990/AVC-3310

Revision.6.4.0

Application terminal: RS-232C/ Ethernet

## Connector specification

### • RS-232C

Connector type: DB-9pin female type, slave straight connection (DCE type)

( 1pin : GND , 2pin : TxD , 3pin : RxD , 5pin : Common(GND) , 4,6,7,8,9pin : NC )

Communication format:


Synchronous system	: Tone step synchronization
Communication system	: A half duplex
Communication speed	: 9600bps
Character length	: 8 bits
Parity control	: None
Start bit	: 1 bit
Stop bit	: 1 bit
Communication procedure	: Non procedural
Communication data length	: 135 bytes (maximum)

Version	Date	Contents	Page
6.4.0		Original	


- **Ethernet**

Connector type : RJ-45(10BASE-T/100BASE-TX)

*Example*



*Example*



Communication format :

Communication system	: A half duplex
Communication speed	: 10Mbps/100Mbps
Communication port	: TCP port 23 (telnet)
Communication data length	: 135bytes (maximum)

## NETWORK SETUP of AVR-3310/AVR-990/AVC-3310

### >Procedure of Network Setup mode.

(1)Press **MENU** button, then System Setup Menu appears on FL-display(and GUI)

(2)Select "Manual Setup > Network Setup > Network Connecting > Detail" .

(3)Set parameters described below.

<DHCP> "ON"---Use this setting when DHCP server is on the local network.

"OFF"---Use this setting when DHCP server is not on the local network.

<IP Address> When <DHCP> sets "OFF", please set IP address.

When <DHCP> sets "ON", you can confirm the IP address that is set by server.

<Subnet Mask> When <DHCP> sets "OFF", please set Subnet Mask.

When <DHCP> sets "ON", you can confirm the Subnet Mask that is set by server.

<Gateway> Set the address of Gateway when Gateway is on the local network.

Do not set this parameter when Gateway is not on the local network.

<Primary DNS> Do not set this parameter.

<Secondary DNS> Do not set this parameter.

<Proxy> Set this parameter "OFF".

### <Network Option: Network Standby Mode>

(1)Press MENU button, then Menu appears on FL-display (and GUI)

(2)Select "Manual Setup > Network Setup > Other > Network Standby"

(3)Set parameters described below.

"ON" ---Use this setting when using the AVR-3310 connected in a network.

"OFF" --- Use this setting when not using the AVR-3310 connected in a network.

This setting is reducing the power consumption in the standby mode.

## Protocol specification

The following three data forms are defined.

- COMMAND** : The message sent to a system(AVR) from a controller(Touch Panel etc.)  
A command to a system is given from a controller.
- EVENT** : The message sent to a controller (Touch Panel etc.) from a system (AVR)  
The result is sent, when a system is operated directly and a state changes.  
\*The form of **EVENT** presupposes that it is the same as that of **COMMAND**.  
\*\*Refer to the following table for the contents of **COMMAND** and **EVENT**.
- RESPONSE** : The message sent to a controller (Touch Panel etc.) from a system (AVR)  
if the 'request command' (**COMMAND+?** +CR (0x0D)) has came from a controller.  
The **RESPONSE** should be sent within 200ms of receiving the **COMMAND**.  
\*The form of **RESPONSE** presupposes that it is the same as that of **EVENT**.

**Basic specification:** The command by ASCII CODE, parameter expression

\*ASCII CODE which can be used is from 0x20 to 0x7F: the alphabet and the number of 0-9, and space (0x20), some signs,  
AND carriage return (0x0D) --- It is used only as a pause sign.

**Command structure:** COMMAND + PARAMETER + CR (0x0D)

COMMAND: ASCII CODE of 2 characters

- Ex.        SI    : Select Input source  
              MS    : surround Mode Setting  
              MV    : Master Volume setting  
              PW    : system PoWer setting

PARAMETER : ASCII CODE (up to 25 characters)

- Ex.        DVD : function name

SUPER STADIUM : surround mode name

\*Special Parameter--- ? : for request command

**The example of a command**

\* <CR> is the meaning of 0x0D.

SIDVD<CR> : Select Input source DVD

MSSTEREO<CR> : surround Mode Set to STEREO

MVUP<CR> : Master Volume UP

PWON<CR> : system PoWer ON

PWSTANDBY<CR> : system PoWer STANDBY

SI?<CR> : Request command for now playing input source >> Return **RESPONSE** 'SI\*\*\*<CR>'

## Others

- A) **COMMAND** is receivable also during transmission of **EVENT**.
- B) Since CHANNEL VOLUME changes simultaneously when the SURROUND MODE changes, the value of the channel volume of all channels returns as **EVENT**.
- C) CHANNEL VOLUME returns the data of ALL channels by the present SURROUND MODE also including an intact channel. In this case, the data of an intact channel is set to "50".
- D) Since SURROUND MODE changes simultaneously when the INPUT source changes, the SURROUND MODE (and also the value of the channel volume of all channels, It described in B) ) returns as **EVENT**.
- E) When SURROUND MODE is the same in between INPUT source change before and after, **EVENT** of SURROUND MODE and CHANNEL VOLUME does NOT return.
- F) Although **EVENT** of SURROUND MODE returns when the present SURROUND MODE is set up again, CHANNEL VOLUME does NOT return.
- G) When SURROUND MODE is changed, before returning SURROUND MODE after change as **EVENT**, the present SURROUND MODE is returned.
- H) The **RESPONSE** should be sent as opposed to the request command by all the commands with which an **EVENT** exists, not need to the another request commands(ex. SV command).
- I) The **PARAMETER** (with **COMMAND** and **RESPONSE**, **EVENT**) of minimum level of MASTER VOLUME defines "99".
- J) If the MASTER VOLUME & CHANNEL VOLUME set with 0.5dB step, the **PARAMETER** (with **COMMAND** and **RESPONSE**, **EVENT**) defines three ASCII characters as bellows.

Ex.   MASTER VOLUME = +1.0dB :       MV81<CR>  
                 +0.5dB :       MV805<CR>  
                  0dB :       MV80<CR>  
                 -0.5dB :       MV795<CR>  
                 -1.0dB :       MV79<CR>  
                    |            |  
                 -79.5dB :       MV005<CR>  
                 -80.0dB :       MV00<CR>  
                 -80.5dB :       MV995<CR>  
                 --- :        MV99<CR>

\* At the \*\*.0dB step, only uses two ASCII characters as **PARAMETER**, same as usual.

- K) 1 seconds later, please transmit the next **COMMAND** after transmitting a power on **COMMAND** ( PWON ).

## COMMAND and PARAMETER list

COMMAND	PARAMETER	function	example
PW	ON	POWER ON/STANDBY change	PWON<CR>
	STANDBY		PWSTANDBY<CR>
	?		PW?<CR>
MV	UP	MASTER VOLUME UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 80=0dB, 99=---(MIN) -80.5=995	MVUP<CR>
	DOWN		MVDOWN<CR>
	**		MV80<CR>
	?		MV?<CR>
CV	FL UP	CHANNEL VOLUME UP/DOWN , direct change to **dB ---FRONT Lch **:38 to 62 by ASCII , 50=0dB ---FRONT Rch **:38 to 62 by ASCII , 50=0dB ---CENTERch **:38 to 62 by ASCII , 50=0dB ---SUBWOOFERch **:00,38 to 62 by ASCII , 50=0dB,00=OFF ---SURROUND Lch **:38 to 62 by ASCII , 50=0dB ---SURROUND Rch **:38 to 62 by ASCII , 50=0dB ---SURROUND BACK Lch (SBch 2SP) **:38 to 62 by ASCII , 50=0dB ---SURROUND BACK Rch (SBch 2SP) **:38 to 62 by ASCII , 50=0dB	CVFL UP<CR>
	FL DOWN		CVFL DOWN<CR>
	FL **		CVFL 50<CR>
	FR UP		CVFR UP<CR>
	FR DOWN		CVFR DOWN<CR>
	FR **		CVFR 50<CR>
	C UP		CVC UP<CR>
	C DOWN		CVC DOWN<CR>
	C **		CVC 50<CR>
	SW UP		CVSW UP<CR>
	SW DOWN		CVSW DOWN<CR>
	SW **		CVSW 50<CR>
	SL UP		CVSL UP<CR>
	SL DOWN		CVSL DOWN<CR>
	SL **		CVSL 50<CR>
	SR UP		CVSR UP<CR>
	SR DOWN		CVSR DOWN<CR>
	SR **		CVSR 50<CR>
	SBL UP		CVSBL UP<CR>
	SBL DOWN		CVSBL DOWN<CR>
	SBL **		CVSBL 50<CR>
	SBR UP		CVSBR UP<CR>
	SBR DOWN		CVSBR DOWN<CR>
	SBR **		CVSBR 50<CR>

MV, CV COMMAND : "\*" parameter uses two or three ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
CV	SB UP	---SURROUND BACKch (SBch 1SP) **:00 to 99 by ASCII , 50=0dB ---FRONT HEIGHT Lch **:00 to 99 by ASCII , 50=0dB ---FRONT HEIGHT Rch **:00 to 99 by ASCII , 50=0dB Return CV Status	CVSB UP<CR>
	SB DOWN		CVSB DOWN<CR>
	SB **		CVSB 50<CR>
	FHL UP		CVFHL UP<CR>
	FHL DOWN		CVFHL DOWN<CR>
	FHL **		CVFHL 50
	FHR UP		CVFHR UP<CR>
	FHR DOWN		CVFHR DOWN<CR>
	FHR **		CVFHR 50
	?		CV?<CR>
MU	ON	OUTPUT MUTE ON/OFF change Return MU Status	MUON<CR>
	OFF		MUOFF<CR>
	?		MU?<CR>
SI	PHONO	Select INPUT source (except North America model)  (North America model Only)  (North America model Only)  (except Japan model) (North America model Only) (except Japan , China model) (except Japan model) (except Japan model) (except Japan model) (except Japan model) (except Japan model) Return SI Status	SIPHONO<CR>
	CD		SICD<CR>
	TUNER		SITUNER<CR>
	DVD		SIDVD<CR>
	HDP		SIHDP<CR>
	TV		SITV<CR>
	SAT/CBL		SISAT/CBL<CR>
	VCR		SIVCR<CR>
	DVR		SIDVR<CR>
	V.AUX		SIV.AUX<CR>
	SIRIUS		SISIRIUS<CR>
	HDRADIO		SIHDRADIO<CR>
	IPOD		SIIPOD<CR>
	NET/USB		SINET/USB<CR>
	RHAPSODY		SIRHAPSODY<CR>
	NAPSTER		SINAPSTER<CR>
	IRADIO		SIIRADIO<CR>
	SERVER		SISERVER<CR>
	FAVORITES		SIFAVORITES<CR>
	USB DIRECT		SIUSB DIRECT<CR>
	?		SI?<CR>

COMMAND	PARAMETER	function	example
ZM	ON	MAIN ZONE ON/OFF change Return ZM Status	ZMON<CR>
	OFF		ZMOFF<CR>
	?		ZM?<CR>
SR	PHONO   USB DIRECT	REC SELECT mode set , and select source ---The name of PARAMETER is the same as that of the time of SI COMMAND.	SRPHONO<CR>   SRUSB DIRECT <CR>
	SOURCE	REC SELECT mode cancel	SRSOURCE<CR>
	?	Return SR Status	SR?<CR>

CV **COMMAND** : "\*" parameter uses two ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
SD	AUTO	set AUTO mode (Priority:HDMI>>DIGITAL>>ANALOG)	SDAUTO<CR>
	HDMI	set force HDMI INPUT mode	SDHDMI<CR>
	DIGITAL	set force DIGITAL INPUT (Optical,Coaxial)mode	SDDIGITAL<CR>
	ANALOG	set force ANALOG INPUT mode	SDANALOG<CR>
	EXT.IN	--Set EXT.IN mode	SDEXT.IN<CR>
	?	Return SD Status	SD?<CR>
DC	AUTO	set DIGITAL INPUT AUTO mode	DCAUTO<CR>
	PCM	set DIGITAL INPUT force PCM mode	DCPCM<CR>
	DTS	set DIGITAL INPUT force DTS mode	DCDTS<CR>
	?	Return DC Status	DC?<CR>
SV	DVD	VIDEO SELECT mode set , and select source	SVDVD<CR>
	HDP		SVHDP<CR>
	TV		SVTV<CR>
	SAT/CBL		SVSAT/CBL<CR>
	VCR		SVVCR<CR>
	DVR		SVDVR<CR>
	V.AUX		SVV.AUX<CR>
	SOURCE	VIDEO SELECT mode cancel	SVSOURCE<CR>
	?	Return SV Status	SV?<CR>
SLP	OFF	MAIN ZONE SLEEP TIMER setting	SLPOFF<CR>
	120		SLP120<CR>
	90		SLP90<CR>
	60		SLP60<CR>
	30		SLP30<CR>
	?	Return SLP Status	SLP?<CR>

COMMAND	PARAMETER	function	example
MS	DIRECT	Select SURROUND mode	MSDIRECT<CR>
	PURE DIRECT		MSPURE DIRECT<CR>
	STEREO		MSSTEREO<CR>
	STANDARD		MSSTANDARD<CR>
	DOLBY DIGITAL		MSDOLBY DIGITAL<CR>
	DTS SURROUND		MSDTS SURROUND<CR>
	7CH STEREO		MS7CH STEREO<CR>
	ROCK ARENA		MSROCK ARENA<CR>
	JAZZ CLUB		MSJAZZ CLUB<CR>
	MONO MOVIE		MSMONO MOVIE<CR>
	MATRIX		MSMATRIX<CR>
	VIDEO GAME		MSVIDEO GAME<CR>
	VIRTUAL		MSVIRTUAL<CR>
	?	Return MS Status	MS?<CR>
	QUICK1	QUICK SELECT 1-5 MODE SELECT	MSQUICK1<CR>
	QUICK2		MSQUICK2<CR>
	QUICK3		MSQUICK3<CR>
	QUICK4		MSQUICK4<CR>
	QUICK5		MSQUICK5<CR>
	QUICK1 MEMORY	QUICK SELECT 1-5 MODE MEMORY	MSQUICK1 MEMORY<CR>
	QUICK2 MEMORY		MSQUICK2 MEMORY<CR>
	QUICK3 MEMORY		MSQUICK3 MEMORY<CR>
	QUICK4 MEMORY		MSQUICK4 MEMORY<CR>
	QUICK5 MEMORY		MSQUICK5 MEMORY<CR>
	QUICK ?	Return MSQUICK Status	MSQUICK ?<CR>

<b>COMMAND</b>	<b>PARAMETER</b>	<i>function</i>	<i>example</i>
VS	ASPNRM	Set Normal mode	VSASPNRM<CR>
	ASPFUL	Set FULL mode	VSASPFUL<CR>
	ASP ?	Return VSASPECT Status	VSASP ?<CR>
	SC48P	Set Resolution to 480p/576p	VSSC48P<CR>
	SC10I	Set Resolution to 1080i	VSSC10I<CR>
	SC72P	Set Resolution to 720p	VSSC72P<CR>
	SC10P	Set Resolution to 1080p	VSSC10P<CR>
	SC10P24	Set Resolution to 1080p:24Hz	VSSC10P24<CR>
	SCAUTO	Set Resolution to AUTO	VSSCAUTO<CR>
	SC ?	Return VSSC Status	VSSC ?<CR>
	SCH48P	Set Resolution to 480p/576p (HDMI)	VSSCH48P<CR>
	SCH10I	Set Resolution to 1080i(HDMI)	VSSCH10I<CR>
	SCH72P	Set Resolution to 720p(HDMI)	VSSCH72P<CR>
	SCH10P	Set Resolution to 1080p(HDMI)	VSSCH10P<CR>
	SCH10P24	Set Resolution to 1080p:24Hz(HDMI)	VSSCH10P24<CR>
	SCHAUTO	Set Resolution to AUTO(HDMI)	VSSCHAUTO<CR>
	SCH ?	Return VSSCH Status(HDMI)	VSSCH ?<CR>
	AUDIO AMP	Set HDMI AUDIO Output to AMP	VSAUDIO AMP<CR>
	AUDIO TV	Set HDMI AUDIO Output to TV	VSAUDIO TV<CR>
	AUDIO ?	Return VSAUDIO Status	VSAUDIO ?<CR>

COMMAND	PARAMETER	function	example
PS	TONE CTRL ON	PARAMETER setting	PSTONE CTRL ON<CR>
	TONE CTRL OFF	TONE CONTROL ON/OFF	PSTONE CTRL OFF<CR>
	TONE CTRL ?	Return PSTONE CONTROL Status	PSTONE CTRL ?<CR>
	SB:MTRX ON	SURROUND BACK SP MODE set	PSSB:MTRX ON<CR>
	SB:PL2X CINEMA		PSSB:PL2X CINEMA<CR>
	SB:PL2X MUSIC		PSSB:PL2X MUSIC<CR>
	SB:ON		PSSB:ON<CR>
	SB:OFF		PSSB:OFF<CR>
	SB: ?	Return PSSB: Status	PSSB: ?<CR>
	CINEMA EQ.ON	CINEMA EQ. ON/OFF	PSCINEMA EQ.ON<CR>
	CINEMA EQ.OFF		PSCINEMA EQ.OFF<CR>
	CINEMA EQ. ?		PSCINEMA EQ. ?<CR>
	MODE: MUSIC	CINEMA / MUSIC / GAME / PL mode change (This parameter can change DOLBY PL2,PL2x,NEO:6 mode.) ---SB=ON : PL2x mode / SB=OFF : PL2 mode --- GAME can change DOLBY PL2 & PL2x mode --- PL can change ONLY DOLBY PL2 mode	PSMODE: MUSIC<CR>
	MODE: CINEMA		PSMODE: CINEMA<CR>
	MODE: GAME		PSMODE: GAME<CR>
	MODE: PRO LOGIC		PSMODE: PRO LOGIC<CR>
	MODE: ?		PSMODE: ?<CR>
	FH:ON	FRONT HEIGHT Output ON/OFF	PSFH:ON<CR>
	FH:OFF		PSFH:OFF<CR>
	FH: ?		PSFH: ?<CR>
	MULTEQ:AUDYSSEY	MultEQ mode direct change	PSMULTEQ: AUDYSSEY<CR>
	MULTEQ:BYP.LR		PSMULTEQ: BYP.LR<CR>
	MULTEQ:FLAT		PSMULTEQ: FLAT<CR>
	MULTEQ:MANUAL		PSMULTEQ: MANUAL<CR>
	MULTEQ:OFF		PSMULTEQ: OFF<CR>
	MULTEQ ?	Return PSMULTEQ: Status	PSMULTEQ: ?<CR>

COMMAND	PARAMETER	function	example
PS	DYNEQ ON	Dynamic EQ = ON	PSDYNEQ ON<CR>
	DYNEQ OFF	Dynamic EQ = OFF	PSDYNEQ OFF<CR>
	DYNEQ ?	Return PSDYNEQ Status	PSDYNEQ ?<CR>
	REFLEV 0	Reference Level Offset=0dB	PSREFLEV 0<CR>
	REFLEV 5	Reference Level Offset=5dB	PSREFLEV 5<CR>
	REFLEV 10	Reference Level Offset=10dB	PSREFLEV 10<CR>
	REFLEV 15	Reference Level Offset=15dB	PSREFLEV 15<CR>
	REFREV ?	Return PSREFLEV Status	PSREFLEV ? <CR>
	DYNVOL ON	Dynamic VOLUME = ON	PSDYNVOL ON<CR>
	DYNVOL OFF	Dynamic VOLUME = OFF	PSDYNVOL OFF<CR>
	DYNVOL ?	Return PSDYNVOL Status	PSDYNVOL ?<CR>
	DYNSET NGT	Dynamic Vol. Setting = Midnight	PSDYNSET NGT<CR>
	DYNSET EVE	Dynamic Vol. Setting = Evening	PSDYNSET EVE<CR>
	DYNSET DAY	Dynamic Vol. Setting = Day	PSDYNSET DAY<CR>
	DYNSET ?	Return PSDYNSET Status	PSDYNSET ?<CR>
	BAS DOWN	**:00 to 99 by ASCII , 50=0dB	PSBAS DOWN<CR>
	BAS **	--AVR-3310/990 can be operated from -6 to +6(44 to 56)	PSBAS 50<CR>
	BAS ?	Return PSBAS Status	PSBAS ?<CR>
	TRE UP	TREBLE UP/DOWN , direct change to **dB	PSTRE UP<CR>
	TRE DOWN	**:00 to 99 by ASCII , 50=0dB	PSTRE DOWN<CR>
	TRE **	--AVR-3310/990 can be operated from -6 to +6(44 to 56)	PSTRE 50<CR>
	TRE ?	Return PSTRE Status	PSTRE ?<CR>
	DRC AUTO	DRC direct change	PSDRC AUTO<CR>
	DRC LOW		PSDRC LOW<CR>
	DRC MID		PSDRC MID<CR>
	DRC HI		PSDRC HI<CR>
	DRC OFF		PSDRC OFF<CR>
	DRC ?	Return PSDRC Status	PSDRC ?<CR>
	DCO OFF	D.COMP direct change	PSDCO OFF<CR>
	DCO LOW		PSDCO LOW<CR>
	DCO MID		PSDCO MID<CR>
	DCO HIGH		PSDCO HIGH<CR>
	DCO ?	Return PSDCO Status	PSDCO ?<CR>

PS COMMAND : "\*" parameter uses two ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
PS	LFE UP	LFE UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0dB, 10=-10dB	PSLFE UP<CR>
	LFE DOWN	---AVR-3310/990 can be operated from 0 to -10	PSLFE DOWN<CR>
	LFE **		PSLFE 10<CR>
	LFE ?	Return PSLFE Status	PSLFE ? <CR>
	EFF UP	EFFECT ON/OFF , EFFECT LEVEL direct change to **dB **:00 to 99 by ASCII , 00=0dB, 10=10dB	PSEFF UP<CR>
	EFF DOWN	---AVR-3310 can be operated from 1 to 15	PSEFF DOWN<CR>
	EFF **		PSEFF **<CR>
	EFF ?	Return PSEFF Status	PSEFF ?<CR>
	DEL UP	DELAY UP/DOWN , direct change to ***dB ***:000 to 999 by ASCII , 000=0ms, 300=300ms	PSDEL UP<CR>
	DEL DOWN	---AVR-3310/990 can be operated from 0 to 300 0-60ms:3ms/Step Over 60ms:10ms/Step	PSDEL DOWN<CR>
	DEL ***		PSDEL ***<CR>
	DEL ?	Return PSDEL Status	PSDEL ?<CR>
	AFD ON	AFDM ON/OFF	PSAFD ON<CR>
	AFD OFF		PSAFD OFF<CR>
	AFD ?	Return PSAFD Status	PSAFD ?<CR>
	PAN ON	PANORAMA ON/OFF	PSPAN ON<CR>
	PAN OFF		PSPAN OFF<CR>
	PAN ?	Return PSPAN Status	PSPAN ?<CR>
	DIM UP	DIMENSION UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0,	PSDIM UP<CR>
	DIM DOWN	---AVR-3310/990 can be operated from 0 to 6	PSDIM DOWN<CR>
	DIM **		PSDIM **<CR>
	DIM ?	Return PSDIM Status	PSDIM ?<CR>
	CEN UP	CENTER WIDTH UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0	PScen UP<CR>
	CEN DOWN	---AVR-3310/990 can be operated from 0 to 7	PScen DOWN<CR>
	CEN **		PScen 07<CR>
	CEN ?	Return PSCEI Status	PScen ?<CR>
	CEI UP	CENTER IMAGE UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0.0	PSCEI UP<CR>
	CEI DOWN	---AVR-3310/990 can be operated from 0.0 to 1.0	PSCEI DOWN<CR>
	CEI **		PSCEI 10<CR>
	CEI?	Return PSCEI Status	OSCEI ?<CR>

PS **COMMAND** : "\*" parameter uses two or three ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
PS	ATT ON	SW ATT ON/OFF	PSATT ON<CR>
	ATT OFF		PSATT OFF<CR>
	ATT ?	Return PSATT Status	PSATT ?<CR>
	SWR ON	SW ON/OFF	PSSWR ON<CR>
	SWR OFF		PSSWR OFF<CR>
	SWR ?	Return PSSWR Status	PSSWR ?<CR>
	RSZ S	ROOM SIZE direct change	PSRSZ S<CR>
	RSZ MS		PSRSZ MS<CR>
	RSZ M		PSRSZ M<CR>
	RSZ ML		PSRSZ ML<CR>
	RSZ L		PSRSZ L<CR>
	RSZ ?	Return PSRSZ Status	PSRSZ ?<CR>
	DELAY UP	AUDIO DELAY UP/DOWN , direct change to ***dB ***:000 to 999 by ASCII , 000=0ms, 200=200ms	PSDELAY UP<CR>
	DELAY DOWN		PSDELAY DOWN<CR>
	DELAY ***		PSDELAY 200<CR>
	RSTR OFF	AUDIO RESTORER direct change	PSRSTR OFF<CR>
	RSTR MODE1		PSRSTR MODE1<CR>
	RSTR MODE2		PSRSTR MODE2<CR>
	RSTR MODE3		PSRSTR MODE3<CR>
	RSTR ?	Return PSRSTR Status	PSRSTR ?<CR>
	FRONT SPA	FRONT SPEAKER direct change	PSFRONT SPA<CR>
	FRONT SPB		PSFRONT SPB<CR>
	FRONT A+B		PSFRONT A+B<CR>
	FRONT?	Return PSFRONT Status	PSFRONT?<CR>

PS **COMMAND** : "\*" parameter uses two or three ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
PV	CN UP	CONTRAST UP/DOWN , direct change to **dB **:44 to 56 by ASCII , 50=0 ---AVR-3310/990 can be operated from -6 to +6(44 to 56) Return PSCN Status	PVCN UP<CR>
	CN DOWN		PVCN DOWN<CR>
	CN **		PVCN 50<CR>
	CN ?		PVCN ?<CR>
	BR UP		PVBR UP<CR>
	BR DOWN		PVBR DOWN<CR>
	BR **		PVBR 12<CR>
	BR ?		PVBR ?<CR>
	CM UP		PVCM UP<CR>
	CM DOWN		PVCM DOWN<CR>
	CM **		PVCM 50<CR>
	CM ?		PVCM ?<CR>
	HUE UP		PVHUE UP<CR>
	HUE DOWN		PVHUE DOWN<CR>
	HUE **		PVHUE 50<CR>
	HUE ?		PVHUE ?<CR>
	DNR OFF	DNR direct change	PVDNR OFF<CR>
	DNR LOW		PVDNR LOW<CR>
	DNR MID		PVDNR MID<CR>
	DNR HI		PVHUE HI<CR>
	DNR ?		PVDNR ?<CR>
	ENH UP	ENHANCER UP/DOWN, direct change to **dB **:00 to 12 by ASCII, 00=0 ---AVR-3310/990 can be operated from 0 to 12	PVENH UP<CR>
	ENH DOWN		PVENH DOWN<CR>
	ENH **		PVENH 12<CR>
	ENH ?		PVENH ?<CR>

PV COMMAND : " \*" parameter uses two ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
Z2	PHONO   USB DIRECT	ZONE2 mode set , and select source ---The name of PARAMETER is the same as that of the time of SI COMMAND.	Z2PHONO<CR>   Z2USB DIRECT<CR>
	SOURCE	ZONE2 mode cancel at AVR-3310/990	Z2SOURCE<CR>
	QUICK1	Z2 QUICK SELECT 1-5 MODE SELECT	Z2QUICK1<CR>
	QUICK2		Z2QUICK2<CR>
	QUICK3		Z2QUICK3<CR>
	QUICK4		Z2QUICK4<CR>
	QUICK5		Z2QUICK5<CR>
	QUICK1 MEMORY	Z2 QUICK SELECT 1-5 MODE MEMORY	Z2QUICK1 MEMORY<CR>
	QUICK2 MEMORY		Z2QUICK2 MEMORY<CR>
	QUICK3 MEMORY		Z2QUICK3 MEMORY<CR>
	QUICK4 MEMORY		Z2QUICK4 MEMORY<CR>
	QUICK5 MEMORY		Z2QUICK5 MEMORY<CR>
	QUICK ?	Return Z2QUICK Status	Z2QUICK ?<CR>
	UP	ZONE2 VOLUME UP/DOWN , direct change to **dB	Z2UP<CR>
	DOWN		Z2DOWN<CR>
	**		Z280<CR>
	ON	ZONE2 ON/OFF change	Z2ON<CR>
	OFF		Z2OFF<CR>
	?		Z2?<CR>
Z2MU	ON	ZONE2 OUTPUT MUTE ON/OFF change	Z2MUON<CR>
	OFF		Z2MUFF<CR>
	?	Return Z2MU Status	Z2MU?<CR>

Z2 **COMMAND** : "\*" parameter uses two ASCII characters. (see page4 J) section)

COMMAND	PARAMETER	function	example
Z2CS	ST	ZONE2 Channel setting <b>---Invalid at AVR-990</b>	Z2CSST
	MONO		Z2CSMONO
	?		Z2CS?
Z2CV	FL UP	ZONE2 CHANNEL VOLUME UP/DOWN , direct change to **dB ---FRONT Lch **:38 to 62 by ASCII , 50=0dB	Z2CVFL UP<CR>
	FL DOWN		Z2CVFL DOWN<CR>
	FL **		Z2CVFL 50<CR>
	FR UP		Z2CVFR UP<CR>
	FR DOWN		Z2CVFR DOWN<CR>
	FR **		Z2CVFR 50<CR>
	?		Z2CV?<CR>
Z2HPF	ON	ZONE2 HPF ON/OFF <b>---Invalid at AVR-990</b>	Z2HPFON<CR>
	OFF		Z2HPFOFF<CR>
	?		Z2HPF?<CR>
Z2PS	BAS UP	ZONE2 BASS UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0dB ---AVR-3310/990 can be operated from -10 to +10(40 to 60) <b>---Invalid at AVR-990</b>	Z2PSBAS UP<CR>
	BAS DOWN		Z2PSBAS DOWN<CR>
	BAS **		Z2PSBAS 50<CR>
	BAS ?		Z2PSBAS ?<CR>
	TRE UP	ZONE2 TREBLE UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0dB ---AVR-3310/990 can be operated from -10 to +10(40 to 60) <b>---Invalid at AVR-990</b>	Z2PSTRE UP<CR>
	TRE DOWN		Z2PSTRE DOWN<CR>
	TRE **		Z2PSTRE 50<CR>
	TRE ?		Z2PSTRE ?<CR>

Z2 **COMMAND** : "\*" parameter uses two ASCII characters. (see page4 J section)

COMMAND	PARAMETER	function	example
Z3	PHONO   USB DIRECT	ZONE3 mode set , and select source ---The name of PARAMETER is the same as that of the time of SI COMMAND.	Z3PHONO<CR>   Z3USB DIRECT<CR>
	SOURCE	ZONE3 mode cancel	Z3SOURCE<CR>
	QUICK1	Z3 QUICK SELECT 1-5 MODE SELECT	Z3QUICK1<CR>
	QUICK2		Z3QUICK2<CR>
	QUICK3		Z3QUICK3<CR>
	QUICK4		Z3QUICK4<CR>
	QUICK5		Z3QUICK5<CR>
	QUICK1 MEMORY	Z3 QUICK SELECT 1-5 MODE MEMORY	Z3QUICK1 MEMORY<CR>
	QUICK2 MEMORY		Z3QUICK2 MEMORY<CR>
	QUICK3 MEMORY		Z3QUICK3 MEMORY<CR>
	QUICK4 MEMORY		Z3QUICK4 MEMORY<CR>
	QUICK5 MEMORY		Z3QUICK5 MEMORY<CR>
	QUICK ?	Return Z3QUICK Status	Z3QUICK ?<CR>
	UP	ZONE3 VOLUME UP/DOWN , direct change to **dB	Z3UP<CR>
	DOWN		Z3DOWN<CR>
	**	**:00 to 99 by ASCII , 80=0dB, 99=---(MIN) 00=-80dB	Z380<CR>
	ON	ZONE3 ON/OFF change at AVR-3310	Z3ON<CR>
	OFF		Z3OFF<CR>
	?	Return Z3 Status	Z2?<CR>
Z3MU	ON	ZONE3 OUTPUT MUTE ON/OFF change	Z3MUON<CR>
	OFF	Z3MUFF<CR>	
	?	Return Z3MU Status	Z3MU?<CR>

Z3 **COMMAND** : "\*" parameter uses two ASCII characters. (see page4 J) section)

Z3 **COMMAND** : Invalid at AVR-990

COMMAND	PARAMETER	function	example
Z3CS	ST	ZONE3 Channel setting Return Z3CS Status	Z3CSST
	MONO		Z3CSMONO
	?		Z3CS?
Z3CV	FL UP	ZONE3 CHANNEL VOLUME UP/DOWN , direct change to **dB ---FRONT Lch **:38 to 62 by ASCII , 50=0dB ZONE3 CHANNEL VOLUME UP/DOWN , direct change to **dB ---FRONT Rch **:38 to 62 by ASCII , 50=0dB	Z3CVFL UP<CR>
	FL DOWN		Z3CVFL DOWN<CR>
	FL **		Z3CVFL 50<CR>
	FR UP		Z3CVFR UP<CR>
	FR DOWN		Z3CVFR DOWN<CR>
	FR **		Z3CVFR 50<CR>
	?		Z3CV?<CR>
Z3HPF	ON	ZONE3 HPF ON/OFF Return Z3HPF Status	Z3HPFON<CR>
	OFF		Z3HPFOFF<CR>
	?		Z3HPF?<CR>
Z3PS	BAS UP	ZONE3 BASS UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0dB ---AVR-3310/990 can be operated from -10 to +10(40 to 60)	Z3PSBAS UP<CR>
	BAS DOWN		Z3PSBAS DOWN<CR>
	BAS **		Z3PSBAS 50<CR>
	BAS ?		Z3PSBAS ?<CR>
	TRE UP	ZONE3 TREBLE UP/DOWN , direct change to **dB **:00 to 99 by ASCII , 00=0dB ---AVR-3310/990 can be operated from -10 to +10(40 to 60)	Z3PSTRE UP<CR>
	TRE DOWN		Z3PSTRE DOWN<CR>
	TRE **		Z3PSTRE 50<CR>
	TRE ?		Z3PSTRE ?<CR>

Z3 **COMMAND** : "\*" parameter uses two ASCII characters. (see page4 J) section)

Z3 **COMMAND** : Invalid at AVR-990

**ANALOG TUNER Control (AVR model only, except North America model)**

COMMAND	PARAMETER	function	example
TF	ANUP	TUNER Frequency UP/DOWN --- ****.** kHz at AM band (>050000 is AM.) *****.** MHz at FM band (<050000 is FM.)	TFANUP<CR>
	ANDOWN		TFANDOWN<CR>
	AN***** (6 digits)		TFAN105000<CR> (1050.00kHz at AM)
	AN?		TFAN?<CR>
TP	ANUP	TUNER PRESET CH UP/DOWN , direct change to No.** ---	TPANUP<CR>
	ANDOWN		TPANDOWN<CR>
	AN** (PRESET No.)		TPANA1<CR> (PRESET No."A1")
	AN?		TPAN?<CR>
	ANMEM		TPANMEM<CR>
TM		TUNER BAND , MODE Select	
	ANAM	---Band set to AM	TMANAM<CR>
	ANFM	---Band set to FM	TMANFM<CR>
	AN?	Return TM Status	TMAN?<CR>
	ANAUTO	---Tuning mode set to AUTO mode	TMANAUTO<CR>
	ANMANUAL	---Tuning mode set to MANUAL mode	TMANMANUAL<CR>

TF, TP, TM **COMMAND** : '\*' parameters can NOT operate when INPUT source isn't TUNER.

**SIRIUS Control(North America model only)**

COMMAND	PARAMETER	function	example
TF	STUP	SIRIUS Channel UP/DOWN --- ***:ST CH No. --- ***:Parental Lock Code Number	TFSTUP<CR>
	STDOWN		TFSTDOWN<CR>
	ST*** (3 digits)		TFST001<CR> (ST001 CH at SIRIUS TUNER)
	STPL**** (4 digits)		TFSTPL1234<CR> (Parental Lock code "1234")
	ST?		TFST?<CR>
TP	STUP	SIRIUS PRESET CH UP/DOWN , direct change to No.**	TPSTUP<CR>
	STDOWN		TPSTDOWN<CR>
	ST** (PRESET No.)		TPSTA1<CR> (PRESET No."A1")
	ST?		TPST?<CR>
	STMEM	SIRIUS PRESET MEMORY	TPSTMEM<CR>
ST	?	Return ST Status - CHANNEL NAME, ARTIST, COMPOSER, TITLE, SIGNAL LEVEL	ST?<CR>

**HD RADIO Control(North America model only)**

COMMAND	PARAMETER	function	example
TF	HDUP	HD Channel UP/DOWN , direct change --- ****.* kHz at AM band (>050000 is AM.) *****.* MHz at FM band (<050000 is FM.) ---HD Multi Cast CH Select(*:0 ~ 8,A:Analog)	TFHDUP<CR>
	HDDOWN		TFHDDOWN<CR>
	HD***** (6 digits)		TFHD105000<CR> (1050.00kHz at AM)
	HDMC*(1 digit)		TFHDMC2<CR>
	HD?		TFHD?<CR>
TP	HDUP	HD PRESET CH UP/DOWN , direct change to No.* ---Band set to AM	TPHDUP<CR>
	HDDOWN		TPHDDOWN<CR>
	HD** (PRESET No.)		TPHDA1<CR> (PRESET No."A1")
	HD?	Return TPHD Status	TPHD?<CR>
	HDMEM	HD PRESET MEMORY	TPHDMEM<CR>
TM	HDAM	HD RADIO BAND , MODE Select ---Band set to AM	TMHDAM<CR>
	HDFM	---Band set to FM	TMHDFM<CR>
	HD?	Return TMHD Status	TMHD?<CR>
	HDAUTOHD	---Tuning mode set to AUTO-HD mode	TMHDAUTOHD<CR>
	HDAUTO	---Tuning mode set to AUTO mode	TMHDAUTO<CR>
	HDMANUAL	---Tuning mode set to MANUAL mode	TMHDMANUAL<CR>
HD	?	Return HD Status ---BAND, STATION NAME, STATION LONG NAME, MULTI CAST CURRENT, MULTI CAST PROGRAM, SIGNAL LEVEL, ARTIST, TITLE, ALBUM, GENRE, PROGRAM TYPE,	HD?<CR>

## Network/iRadio/mServer/USB/Rhapsody/Napster Extended Control

COMMAND	PARAMETER	function	example
SI	USB	Select INPUT source NET/USB and USB Start Playback	SIUSB<CR>
Z2	USB	Select ZONE-2 source NET/USB and USB Start Playback	Z2USB<CR>
Z3	USB	Select ZONE-3 source NET/USB and USB Start Playback	Z3USB<CR>
NS	90	"Cursor Up" Control	NS90<CR>
	91	"Cursor Down" Control	NS91<CR>
	92	"Cursor Left" Control	NS92<CR>
	93	"Cursor Right" Control	NS93<CR>
	94	"Enter (Play/Pause)" Control	NS94<CR>
	9A	"Play" Control	NS9A<CR>
	9B	"Pause" Control (USB/mServer/Rhapsody)	NS9B<CR>
	9C	"Stop" Control	NS9C<CR>
	9D	"Skip Plus" Control (USB/mServer/Rhapsody/Napster)	NS9D<CR>
	9E	"Skip Minus" Control (USB/mServer/Rhapsody/Napster)	NS9E<CR>
	9H	"Repeat One" (USB/mServer/Rhapsody/Napster)	NS9H<CR>
	9I	"Repeat All"- (USB/mServer/Rhapsody/Napster))	NS9I<CR>
	9J	"Repeat Off" (USB/mServer/Rhapsody/Napster)	NS9J<CR>
	9K	"Random On/Repeat ALL" (USB/mServer/Rhapsody/Napster)	NS9K<CR>
	9M	"Random Off" (USB/mServer/Rhapsody/Napster)	NS9M<CR>
	9X	"Page Up" Control	NS9X<CR>
	9Y	"Page Down" Control	NS9Y<CR>

<b>COMMAND</b>	<b>PARAMETER</b>	function	example
NSA		Return Onscreen Display Information List (ASCII CODE Character)	NSA<CR> (Return NSA0-NSA8, Refer to Page 43 )
NSE		Request Onscreen Display Information List (UTF-8 CODE Character)	NSE<CR> (Return NSE0-NSE8, Refer to Page 44 )
NSB	**	"Direct Preset CH Play"	NSB00<CR> ( **:00-55,00=A1, 01=A2,B1=08,G8=55 )
NSC	**	"Direct Preset CH Memory" (iRadio/mServer only)	NSC00<CR> ( **:00-55,00=A1, 01=A2,B1=08,G8=55 )
NSD	*	"Direct Character Search" (except Napster)	NSD0<CR> ( *:0-9,A-Z )

## iPod dock Extended Control

iPod Dock which AVR-3310/AVR-990/AVC-3310 can connect with is ASD-1R/11R.

COMMAND	PARAMETER	function	example
IP	90	"Cursor Up" Control	IP90<CR>
	91	"Cursor Down" Control	IP91<CR>
	92	"Cursor Left" Control	IP92<CR>
	93	"Cursor Right" Control	IP93<CR>
	94	"Enter (Play/Pause)" Control	IP94<CR>
	9A	"Play/Pause" Control	IP9A<CR>
	9C	"Stop" Control	IP9C<CR>
	9D	"Skip Plus" Control	IP9D<CR>
	9E	"Skip Minus" Control	IP9E<CR>
	9F	"Manual Search Plus" Control	IP9F<CR>
	9G	"Manual Search Minus" Control	IP9G<CR>
	9H	"Repeat One" Control	IP9H<CR>
	9I	"Repeat All" Control	IP9I<CR>
	9J	"Repeat Off" Control	IP9J<CR>
	9K	"Shuffle Songs" Control	IP9K<CR>
	9L	"Shuffle Album" Control	IP9L<CR>
	9M	"Shuffle Off" Control	IP9M<CR>
	9N	"MENU" Control	IP9N<CR>
	9P	Switch the "Browse Mode" Control	IP9P<CR>
	9Q	Switch the "Remote Mode" Control	IP9Q<CR>
	9X	"Page Up" Control	IP9X<CR>
	9Y	"Page Down" Control	IP9Y<CR>
IPA		Return Onscreen Display Information List  (Return IPA0-IPA9 Refer to Page 45)	IPA<CR> (Return IPA0-IPA9 Refer to Page 45)
IPE		Request Onscreen Display Information List(iPOD) (UTF-8 CODE Character )	IPE<CR> (Return IPE0-IPE9. Refer to Page 48 )

### **Cursor/Enter/Menu(Setup)**

<b>COMMAND</b>	<b>PARAMETER</b>	<b>function</b>	<b>example</b>
MN	CUP	"Cursor Up" Control	MNCUP<CR>
	CDN	"Cursor Down" Control	MNCDN<CR>
	CL/T	"Cursor Left" Control	MNCLT<CR>
	CRT	"Cursor Right" Control	MNCRT<CR>
	ENT	"Enter" Control	MNENT<CR>
	RTN	"RETURN" Control	MNRTN<CR>
	MEN ON	"GUI Menu ON" Control	MNMEN ON<CR>
	MEN OFF	"GUI Menu OFF" Control	MNMEN OFF<CR>
	SRC ON	"GUI Source Select Menu ON" Control	MNSRC ON<CR>
	SRC OFF	"GUI Source Select Menu OFF" Control	MNSRC OFF<CR>

### **Remote Lock/Panel Lock**

<b>COMMAND</b>	<b>PARAMETER</b>	<b>function</b>	<b>example</b>
SY	REMOTE LOCK ON	REMOTE CONTROL LOCK ON/OFF	SYREMOTE LOCK ON<CR>
	REMOTE LOCK OFF		SYREMOTE LOCK OFF<CR>
	PANEL LOCK ON	PANEL BUTTON(Except MASTER VOL.)CONTROL LOCK ON PANEL BUTTON & MASTER VOL. CONTROL LOCK ON PANEL BUTTUM & MASTER VOL. CONTROL LOCK OFF	SYPANEL LOCK ON<CR>
	PANEL+V LOCK ON		SYPANEL+V LOCK ON<CR>
	PANEL LOCK OFF		SYPANEL LOCK OFF<CR>

### **UPGRADE ID Display**

<b>COMMAND</b>	<b>PARAMETER</b>	<b>function</b>	<b>example</b>
UG	IDN	ID Number for UPGRADE is displayed on FL Display	UGIDN<CR>

## EVENT(or RESPONSE) and PARAMETER list

EVENT	PARAMETER	function	example
PW	ON	POWER ON/STANDBY change	PWON<CR>
	STANDBY		PWSTANDBY<CR>
MV	**	MASTER VOLUME change , **:00 to 99 by ASCII 98 = +18dB(MAX) 80 = 0dB 00 = -80dB 99 = ---(MIN) 995= -80.5dB	MV80<CR>
CV	FL **	CHANNEL VOLUME change , **:00,38 to 62 by ASCII 62 = +12dB(MAX) 50 = 0dB 38 = -12dB(MIN) 00 = OFF (define ONLY SWch in DIRECT mode.)  (at SBch 2SP) (at SBch 2SP) (at SBch 1SP) FRONT HEIGHT Lch FRONT HEIGHT Rch	CVFL 50<CR>
	FR **		CVFR 50<CR>
	C **		CVC 50<CR>
	SW **		CVSW 50<CR>
	SL **		CVSL 50<CR>
	SR **		CVSR 50<CR>
	SBL **		CVSBL 50<CR>
	SBR **		CVSBR 50<CR>
	SB **		CVSB 50<CR>
	FHL **		CVFHL 50<CR>
MU	ON	OUTPUT MUTE ON/OFF change	MUON<CR>
	OFF		MUOFF<CR>
SI	PHONO	INPUT source change ( Except North America model)	SIPHONO<CR>
	CD		SICD<CR>
	TUNER		SITUNER<CR>
	DVD		SIDVD<CR>
	HDP		SIHDP<CR>
	TV		SITV<CR>
	SAT/CBL		SISAT/CBL<CR>
	VCR		SIVCR<CR>
	DVR		SIDVR<CR>
	V.AUX		SIV.AUX<CR>

\*RES. : NOT returns '\*\*' parameters as **RESPONSE**.

The **PARAMETER** of MV, CV **EVENT** : Uses two or three ASCII characters. (see page4 J) section)

EVENT	PARAMETER	function	example
SI	SIRIUS	(North America model Only)	SISIRIUS<CR>
	HDRADIO	(North America model Only)	SIHDRADIO<CR>
	IPOD		SIIPOD<CR>
	RHAPSODY	(North America model Only)	SIRHAPSODY<CR>
	NAPSTER	(except Japan , China model)	SINAPSTER<CR>
	IRADIO	(except Japan model)	SIIRADIO<CR>
	SERVER	(except Japan model)	SISERVER<CR>
	FAVORITES	(except Japan model)	SIFAVORITES<CR>
	USB DIRECT	(except Japan model)	SIUSB DIRECT<CR>
	USB	( Input Source Change to USB with Play)	SIUSB <CR>
ZM	ON	MAIN ZONE ON/OFF change	ZMON<CR>
	OFF		ZMOFF<CR>
SR	PHONO	REC SELECT source change ---The name of PARAMETER is the same as that of the time of SI COMMAND.	SRPHONO<CR>
	SERVER		 SRSERVER <CR>
	SOURCE	REC SELECT mode cancel	SRSOURCE<CR>
SD	AUTO	INPUT mode change ---Set EXT.IN mode	SDAUTO<CR>
	HDMI		SDHDMI<CR>
	DIGITAL		SDDIGITAL<CR>
	ANALOG		SDANALOG<CR>
	EXT. IN		SDEXT. IN<CR>
DC	AUTO	DIGITAL INPUT mode change	DCAUTO<CR>
	PCM		DCPCM<CR>
	DTS		DCDTS<CR>
SV	DVD	VIDEO SELECT mode source change	SVDVD<CR>
	HDP		SVHDP<CR>
	TV		SVTV<CR>
	SAT/CBL		SVSAT/CBL<CR>
	VCR		SVVCR<CR>
	DVR		SVDVR<CR>
	V.AUX		SVV. AUX<CR>
	SOURCE		SVSOURCE<CR>
SLP	OFF	MAIN ZONE SLEEP TIMER setting change	SLPOFF<CR>
	120		SLP120<CR>
	90		SLP90<CR>
	60		SLP60<CR>
	30		SLP30<CR>

EVENT	PARAMETER	function	example
MS	DIRECT	SURROUND mode change	MSDIRECT<CR>
	PURE DIRECT		MSPURE DIRECT<CR>
	STEREO		MSSTEREO<CR>
	MULTI CH IN		MSMULTI CH IN<CR>
	M CH IN+DOLBY EX		MSM CH IN+DOLBY EX<CR>
	M CH IN+PL2X C		MSM CH IN+PL2X C<CR>
	M CH IN+PL2X M		MSM CH IN+PL2X M<CR>
	M CH IN+PL2Z H		MSM CH IN+PL2Z H<CR>
	MULTI CH DIRECT		MSMULTI CH DIRECT<CR>
	M CH DRCT+DOLBY EX		MSM CH DRCT+DOLBY EX <CR>
	M CH DRCT+PL2X C		MSM CH DRCT+PL2X C <CR>
	M CH DRCT+PL2X M		MSM CH DRCT+PL2X M <CR>
	M CH DRCT+PL2Z H		MSM CH DRCT+PL2Z H <CR>
	MULTI CH PURE D		MSMULTI CH PURE D<CR>
	M CH PURE D+DOLBY EX		MSM CH PURE D+DOLBY EX<CR>
	M CH PURE D+PL2X C		MSM CH PURE D+PL2X C <CR>
	M CH PURE D+PL2X M		MSM CH PURE D+PL2X M <CR>
	M CH PURE D+PL2Z H		MSM CH PURE D+PL2Z H<CR>
	MULTI CH IN 7.1		MSMULTI CH IN 7.1<CR>
	M DIRECT 7.1		MSM DIRECT 7.1<CR>
	M CH PURE D 7.1		MSM CH PURE D 7.1<CR>
	DOLBY PRO LOGIC		MSDOLBY PRO LOGIC<CR>
	DOLBY PL2 C		MSDOLBY PL2 C<CR>
	DOLBY PL2 M		MSDOLBY PL2 M<CR>
	DOLBY PL2 G		MSDOLBY PL2 G<CR>
	DOLBY PL2X C		MSDOLBY PL2X C<CR>
	DOLBY PL2X M		MSDOLBY PL2X M<CR>
	DOLBY PL2X G		MSDOLBY PL2X G<CR>
	DOLBY PL2Z H		MSDOLBY PL2Z H<CR>
	DOLBY DIGITAL		MSDOLBY DIGITAL<CR>
	DOLBY D EX		MSDOLBY D EX<CR>
	DOLBY D+PL2X C		MSDOLBY D+PL2X C<CR>
	DOLBY D+PL2X M		MSDOLBY D+PL2X M<CR>
	DOLBY D+PL2Z H		MSDOLBY D+PL2Z H<CR>

EVENT	PARAMETER	function	example
MS	DTS NEO:6 C	( JAPAN model Only )	MSDTS NEO:6 C<CR>
	DTS NEO:6 M		MSDTS NEO:6 M<CR>
	DTS SURROUND		MSDTS SURROUND<CR>
	DTS ES DSCRT6.1		MSDTS ES DSCRT6.1<CR>
	DTS ES MTRX6.1		MSDTS ES MTRX6.1<CR>
	DTS+NEO:6		MSDTS+NEO:6<CR>
	DTS+PL2X C		MSDTS+PL2X C<CR>
	DTS+PL2X M		MSDTS+PL2X M<CR>
	DTS+PL2Z H		MSDTS+PL2Z H<CR>
	DTS96/24		MSDTS96/24<CR>
	DTS96 ES MTRX		MSDTS96 ES MTRX<CR>
	5CH STEREO		MS5CH STEREO<CR>
	7CH STEREO		MS7CH STEREO<CR>
	ROCK ARENA		MSROCK ARENA<CR>
	JAZZ CLUB		MSJAZZ CLUB<CR>
	MONO MOVIE		MSMONO MOVIE<CR>
	MATRIX		MSMATRIX<CR>
	VIDEO GAME		MSVIDEO GAME<CR>
	VIRTUAL		MSVIRTUAL<CR>
	MPEG2 AAC		MSMPEG2 AAC<CR>
	AAC+DOLBY EX		MSAAC+DOLBY EX<CR>
	AAC+PL2X C		MSAAC+PL2X C<CR>
	AAC+PL2X M		MSAAC+PL2X M<CR>
	AAC+PL2Z H		MSAAC+PL2Z H<CR>
	DOLBY D+	( DOLBY TRUEHD )	MSDOLBY D+<CR>
	DOLBY D+ +EX		MSDOLBY D+ +EX<CR>
	DOLBY D+ +PL2X C		MSDOLBY D+ +PL2X C<CR>
	DOLBY D+ +PL2X M		MSDOLBY D+ +PL2X M<CR>
	DOLBY D+ +PL2Z H		MSDOLBY D+ +PL2Z H<CR>
	DOLBY HD		MSDOLBY HD<CR>
	DOLBY HD+EX		MSDOLBY HD+EX<CR>
	DOLBY HD+PL2X C		MSDOLBY HD+PL2X C<CR>
	DOLBY HD+PL2X M		MSDOLBY HD+PL2X M<CR>
	DOLBY HD+PL2Z H		MSDOLBY HD+PL2Z H<CR>

EVENT	PARAMETER	function	example
MS	DTS HD		MSDTS HD<CR>
	DTS HD MSTR		MSDTS HD MSTR<CR>
	DTS EXPRESS		MSDTS EXPRESS<CR>
	DTS HD+NEO:6		MSDTS HD+NEO:6<CR>
	DTS HD+PL2X C		MSDTS HD+PL2X C<CR>
	DTS HD+PL2X M		MSDTS HD+PL2X M<CR>
	DTS HD+PL2Z H		MSDTS HD+PL2Z H<CR>
	DTS ES 8CH DSCRT		MSDTS ES 8CH DSCRT<CR>
	EXT. IN		MSEXTR. IN<CR>
	PURE DIRECT EXT		MSPURE DIRECT EXT<CR>
	QUICK1	QUICK SELECT mode change	MSQUICK1<CR>
	QUICK2		MSQUICK2<CR>
	QUICK3		MSQUICK3<CR>
	QUICK4		MSQUICK4<CR>
	QUICK5		MSQUICK5<CR>
	QUICK0	--- QUICK 1(or 2,3,4,5) Change QUICK OFF	MSQUICK0<CR>

EVENT	PARAMETER	function	example
VS	ASPNRM	ASPECT setting change	VSAСПNRM<CR>
	ASPFUL		VSAСПFUL<CR>
	SC48P	Resolution setting change	VSSC48P<CR>
	SC10I		VSSC10I<CR>
	SC72P		VSSC72P<CR>
	SC10P		VSSC10P<CR>
	SC10P24		VSSC10P24<CR>
	SCHAUTO	Resolution(HDMI) setting change	VSSCHAUTO<CR>
	SCH48P		VSSCH48P<CR>
	SCH10I		VSSCH10I<CR>
	SCH72P		VSSCH72P<CR>
	SCH10		VSSCH10P<CR>
	SCH10P24		VSSCH10P24<CR>
	SCHAUTO		VSSCHAUTO<CR>
	AUDIO AMP	HDMI AUDIO Output setting change	VSAUDIO AMP<CR>
	AUDIO TV		VSAUDIO TV<CR>

EVENT	PARAMETER	function	example
PS	TONE CTRL ON	TONE CTRL ON/OFF change	PSTONE CTRL ON<CR>
	TONE CTRL OFF		PSTONE CTRL OFF<CR>
	SB:MTRX ON	SURROUND BACK MODE change	PSSB:MTRX ON<CR>
	SB:PL2x C		PSSB:PL2X C<CR>
	SB:PL2x M		PSSB:PL2X M<CR>
	SB:ON		PSSB:ON<CR>
	SB:OFF		PSSB:OFF<CR>
	SB:ESDSCRT		PSSB:ESDSCRT<CR>
	SB:ESMTRX		PSSB:ESMTRX<CR>
	SB:DSCRT ON		PSSB:DSCRT ON<CR>
	CINEMA EQ.ON	CINEMA EQ. ON/OFF Change	PSCINEMA EQ.ON<CR>
	CINEMA EQ.OFF		PSCINEMA EQ.OFF<CR>
	MODE: MUSIC	CINEMA / MUSIC / GAME / PL / HEIGHT mode change	PSMODE: MUSIC<CR>
	MODE: CINEMA		PSMODE: CINEMA<CR>
	MODE: GAME		PSMODE: GAME<CR>
	MODE: PRO LOGIC		PSMODE: PRO LOGIC<CR>
	MODE: HEIGHT		PSMODE: HEIGHT<CR>
	FH:ON	FRONT HEIGHT Output Change	PSFH:ON<CR>
	FH:OFF		PSFH:OFF<CR>
	MULTEQ: AUDYSSEY	MultEQ mode direct change	PSMULTEQ: AUDYSSEY<CR>
	MULTEQ: BYP.LR		PSMULTEQ: BYP.LR<CR>
	MULTEQ: FLAT		PSMULTEQ: FLAT<CR>
	MULTEQ: MANUAL		PSMULTEQ: MANUAL<CR>
	MULTEQ: OFF		PSMULTEQ: OFF<CR>
	DYNEQ ON	Dynamic EQ direct change	PSDYNEQ ON<CR>
	DYNEQ OFF		PSDYNEQ OFF<CR>
	REFLEV 0	Reference Level Offset direct change	PSREFLEV 0<CR>
	REFLEV 5		PSREFLEV 5<CR>
	REFLEV 10		PSREFLEV 10<CR>
	REFLEV 15		PSREFLEV 15<CR>

EVENT	PARAMETER	function	example
PS	DYNVOL ON	Dynamic VOLUME direct change	PSDYNVOL ON<CR>
	DYNVOL OFF		PSDYNVOL OFF<CR>
	DYNSET NGT	DYNAMIC VOLUME SETTING direct change	PSDYNSET NGT<CR>
	DYNSET EVE		PSDYNSET EVE<CR>
	DYNSET DAY		PSDYNSET DAY<CR>
	BAS **	BASS change	PSBAS 50<CR>
	TRE **	TREBLE change	PSTRE 50<CR>
	DRC AUTO	DRC change	PSDRC AUTO<CR>
	DRC LOW		PSDRC LOW<CR>
	DRC MID		PSDRC MID<CR>
	DRC HI		PSDRC HI<CR>
	DRC OFF		PSDRC OFF<CR>
	DCO OFF	D.COMP change	PSDCO OFF<CR>
	DCO LOW		PSDCO LOW<CR>
	DCO MID		PSDCO MID<CR>
	DCO HIGH		PSDCO HIGH<CR>
	LFE **	LFE change	PSLFE 10<CR>
	EFF **	EFFECT LEVEL change	PSEFF **<CR>
	DEL ***	DELAY change	PSDEL ***<CR>
	AFD ON	AFDM change	PSAFD ON<CR>
	AFD OFF		PSAFD OFF<CR>
	PAN ON	PANORAMA change	PSPAN ON<CR>
	PAN OFF		PSPAN OFF<CR>
	DIM **	DIMENSION change	PSDIM **<CR>
	CEN **	CENTER WIDTH change	PSCEN 07<CR>
	CEI **	CENTER IMAGE change	PSCEI 10<CR>
	ATT ON	SW ATT change	PSATT ON<CR>
	ATT OFF		PSATT OFF<CR>
	SWR ON	SW ON/OFF change	PSSWR ON<CR>
	SWR OFF		PSSWR OFF<CR>

EVENT	PARAMETER	function	example
PS	RSZ S	ROOM SIZE change	PSRSZ S<CR>
	RSZ MS		PSRSZ MS<CR>
	RSZ M		PSRSZ M<CR>
	RSZ ML		PSRSZ ML<CR>
	RSZ L		PSRSZ L<CR>
	DELAY ***	AUDIO DELAY change, ***:000 to 999 by ASCII ---AVR-3310 : 200=200ms (MAX) 100=100ms, 000=0ms	PSDELAY 200<CR>
	RSTR OFF	AUDIO RESTORER change	PSRSTR OFF<CR>
	RSTR MODE1		PSRSTR MODE1<CR>
	RSTR MODE2		PSRSTR MODE2<CR>
	RSTR MODE3		PSRSTR MODE3<CR>
	FRONT SPA	FRONT SPEAKER change	PSFRONT SPA<CR>
	FRONT SPB		PSFRONT SPB<CR>
	FRONT A+B		PSFRONT A+B<CR>
PV	CN **	CONTRAST change	PVCN 50<CR>
	BR **	BRIGHTNESS Change	PVBR 12<CR>
	CM **	CROMA LEVEL change	PVCM 50<CR>
	HUE **	Hue Change	PVHUE 50<CR>
	DNR OFF	DNR change	PVDNR OFF<CR>
	DNR LOW		PVDNR LOW<CR>
	DNR MID		PVDNR MID<CR>
	DNR HI		PVHUE HI<CR>
	ENH **	ENHANCER change	PVENH 12<CR>

EVENT	PARAMETER	function	example
Z2	PHONO   USB DIRECT	ZONE2 source change ---The name of PARAMETER is the same as that of the time of SI COMMAND.	Z2PHONO<CR>   Z2USB DIRECT <CR>
	SOURCE	ZONE2 mode cancel	Z2SOURCE<CR>
	QUICK1	ZONE2 QUICK SELECT mode change	Z2QUICK1<CR>
	QUICK2		Z2QUICK2<CR>
	QUICK3		Z2QUICK3<CR>
	QUICK4		Z2QUICK4<CR>
	QUICK5		Z2QUICK5<CR>
	QUICK0	---Z2 QUICK 1(or 2, 3, 4, 5) Change Z2 QUICK OFF	Z2QUICK0<CR>
	**	ZONE2 VOLUME change , **:00 to 99 by ASCII 98 = +18dB(MAX) 80 = 0dB 10 = -70dB 0=-80dB 99 = ---(MIN)	Z280<CR>
	ON	ZONE2 ON/OFF change	Z2ON<CR>
	OFF		Z2OFF<CR>
Z2MU	ON	ZONE2 OUTPUT MUTE ON/OFF change	Z2MUON<CR>
	OFF		Z2MUFF<CR>
Z2CS	ST	ZONE2 Channel setting ---AVR990:Disable	Z2CSST<CR>
	MONO		Z2CSMONO<CR>
Z2CV	FL **	**:38 to 62 by ASCII , 50=0dB **:38 to 62 by ASCII , 50=0dB	Z2CVFL 50<CR>
	FR **		Z2CVFR 50<CR>
Z2HPF	ON	ZONE2 HPF ON/OFF change ---AVR990:Disable	Z2HPFON<CR>
	OFF		Z2HPFOFF<CR>
Z2PS	BAS **	ZONE2 BASS change ---AVR990:Disable	Z2PSBAS 00<CR>
	TRE **	ZONE2 TEBLE change ---AVR990:Disable	Z2PSTRE 00<CR>

The **PARAMETER** of Z2 **EVENT** : Uses two ASCII characters. (see page4 J) section)

EVENT	PARAMETER	function	example
Z3	PHONO   USB DIRECT	ZONE3 source change ---The name of PARAMETER is the same as that of the time of SI COMMAND.	Z3PHONO<CR>   Z3USB DIRECT<CR>
	SOURCE	ZONE3 mode cancel ---AVR990:Disable	Z3SOURCE<CR>
	QUICK1	ZONE3 QUICK SELECT mode change ---AVR990:Disable	Z3QUICK1<CR>
	QUICK2		Z3QUICK2<CR>
	QUICK3		Z3QUICK3<CR>
	QUICK4		Z3QUICK4<CR>
	QUICK5		Z3QUICK5<CR>
	QUICK0		Z3QUICK0<CR>
	**	MULTI ZONE-3 VOLUME change , **:00 to 99 by ASCII 98 = +18dB(MAX) 80 = 0dB 10 = -70dB 00=-80dB 99 = ---(MIN) ---AVR990:Disable	Z380<CR>
	ON	MULTI ZONE-3 ON/OFF change ---AVR990:Disable	Z3ON<CR>
	OFF		Z3OFF<CR>
Z3MU	ON	ZONE3 OUTPUT MUTE ON/OFF change ---AVR990:Disable	Z3MUON<CR>
	OFF		Z3MUFF<CR>
Z3CS	ST	ZONE3 Channel setting ---AVR990:Disable	Z3CSST<CR>
	MONO		Z3CSMONO<CR>
Z3CV	FL **	**:38 to 62 by ASCII , 50=0dB ---AVR990:Disable **:38 to 62 by ASCII , 50=0dB ---AVR990:Disable	Z3CVFL 50<CR>
	FR **		Z3CVFR 50<CR>
Z3HPF	ON	ZONE3 HPF ON/OFF change ---AVR990:Disable	Z3HPFON<CR>
	OFF		Z3HPFOFF<CR>
Z3PS	BAS **	ZONE3 BASS change ---AVR990:Disable	Z3PSBAS 50<CR>
	TRE **	ZONE3 TREBLE change ---AVR990:Disable	Z3PSTRE 50<CR>

The **PARAMETER** of Z3 **EVENT** : Uses two ASCII characters. (see page4 J) section)

**ANALOG TUNER Control (AVR model only.except North America model)**

EVENT	PARAMETER	function	example
TF	AN***** (6 digits)	TUNER Frequency change  --- ****.* kHz at AM band *****.* MHz at FM band	TFAN105000<CR>  (1050.00kHz at AM)
TP	AN**(PRESET No.)	TUNER PRESET change to No.**	TPANA1<CR> (PRESET No."A1")
TM	ANAM	TUNER BAND , MODE change  ---Band set to AM	TMANAM<CR>
	ANFM	---Band set to FM	TMANFM<CR>
	ANAUTO	---Tuning mode set to AUTO mode	TMANAUTO<CR>
	ANMANUAL	---Tuning mode set to MANUAL mode	TMANMANUAL<CR>

## SIRIUS Control (North America Model Only)

EVENT	PARAMETER	function	example
TF	ST*** (3 digits)	--- ***:ST CH No.	TFST001<CR> (ST001 CH at SIRIUS TUNER)
	STPL ON	Parental Lock Status "ON"	TFSTPL ON<CR>
	STPL OFF	Parental Lock Status "OFF"	TFSTPL OFF<CR>
	STUL OK	Unlocking is successful	TFSTUL OK<CR>
	STUL NG	Unlocking is failed	TFSTUL NG<CR>
	STCH SUB	Subscribed channel	TFSTCH SUB<CR>
	STCH UNS	Unsubscribed channel	TFSTCH UNS<CR>
	STMP VAL	Valid Channel	TFSTMP VAL<CR>
	STMP INV	Invalid Channel	TFSTMP INV<CR>
TP	ST** (PRESET No.)	SIRIUS PRESET change to No.**	TPSTA1<CR> (PRESET No. "A1")
ST	CH NAME ***** (20 digits)	SIRIUS CH NAME change	STCH NAME LONG CHANNEL NAM<CR>
	ARTIST ***** (36 digits)	SIRIUS ARTIST NAME change	STARTIST High and mighty color <CR>
	TITLE ***** (36 digits)	SIRIUS TITLE NAME change	STTITLE Memory Crysis <CR>
	COMPOSER ***** (36 digits)	SIRIUS COMPOSER NAME change	STCOMPOSER High and mighty color <CR>
	ID ***** (12 digits)	SIRIUS ID(SR000 Selected)	STID 123456789012<CR>
	SIGNAL EXCELLENT	SIRIUS ANTENNA SIGNAL STATUS change	STSIGNAL EXCELLENT<CR>
	SIGNAL GOOD		STSIGNAL GOOD<CR>
	SIGNAL WEAK		STSIGNAL WEAK<CR>
	SIGNAL NOSIGNAL		STSIGNAL NOSIGNAL<CR>

## HD RADIO Control(North America model only)

EVENT	PARAMETER	function	example
TF	HD***** (6 digits)	--- *****.* kHz at AM band (>050000 is AM.) *****.* MHz at FM band (<050000 is FM.)	TPHD105000<CR> (1050.00kHz at AM)
	HDMC*(1 digit)	---HD Multi Cast CH change(*:0~8,A:Analog)	TFHDMC2<CR>
TP	HD** (PRESET No.)	HD PRESET change to No.**	TPHDA1<CR> (PRESET No."A1")
TM	HDAM	HD RADIO BAND , MODE change ---Band set to AM	TMHDAM<CR>
	HDFM	---Band set to FM	TMHDFM<CR>
	HDAUTOHD	---Tuning mode set to AUTO-HD mode	TMHDAUTOHD<CR>
	HDAUTO	---Tuning mode set to AUTO mode	TMHDAUTO<CR>
	HDMANUAL	---Tuning mode set to MANUAL mode	TMHDMANUAL<CR>
HD	ST NAME (8 digits)	HD STATION NAME change	HDST NAME *****<CR>
	STL NAME (56 digits)	HD STATION LONG NAME change	HDSTL NAME (56 digits)<CR>
	SIG LEV * (1 digit)	HD ANTENNA SIGNAL STATUS change	HDSIG LEV 0<CR> HDSIG LEV 1<CR> HDSIG LEV 2<CR> HDSIG LEV 3<CR> HDSIG LEV 4<CR> HDSIG LEV 5<CR> HDSIG LEV 6<CR>
	MLT CURRENT * (1 digit)	HD MULTI CAST CURRENT CH change	HDMLT CURRENT *<CD>
	MLT CAST CH (8 digits)	HD MULTI CAST CH change	HDMLT CAST CH *****<CR>
	PTY(18 digits)	HD PROGRAM TYPE change	HDPTY (18 digits)<CR>
	ARTIST(40 digits)	HD ARTIST NAME change	HDARTIST (40 digits)<CR>
	TITLE(40 digits)	HD TITLE NAME change	HDTITLE (40 digits)<CR>
	ALBUM(40 digits)	HD ALBUM NAME change	HDALBUM (40 digits)<CR>
	GENRE(23 digits)	HD GANRE change	HDGENRE (23 digits)<CR>
	MODE	HD MODE(ANALOG/DIGITAL)	HD MODE ANALOG<CR> HD MODE DIGITAL<CR>

## Network/iRadio/mServer/USB/Rhapsody/Napster Extended Control

EVENT	PARAMETER	function	
NSA		Onscreen Display Information is Answered By the NSA Command.	
0		Display Line1 Information	NSA0*****_????? *:Character Length MAX96
1		Display Line3 Information	NSA1 *****_????? _:*Null
2		Display Line4 Information	NSA2 *****_????? _:*Exclusion(The character after Null should be disregarded)
3		Display Line5 Information	NSA3 *****_????? _:*Cursor&Playable Music Information Data(1Byte)
4		Display Line6 Information	NSA4 *****_????? _:*Bit1:Playable Music =1
5		Display Line7 Information	NSA5 *****_????? _:*Bit2,3:Don't Care
6		Display Line8 Information	NSA6 *****_????? _:*Bit4:CURSOR SELECT=1
7		Display Line9 Information	NSA7*****_????? _:*Bit5,6,7,8:Don't Care
8		Display Line10 Information	NSA8*****_????? _:*Bit1:Playable Music =1 _:*Bit2,3:Don't Care _:*Bit4:CURSOR SELECT=1 _:*Bit5,6,7,8:Don't Care
			<example> NSA0Now Playing USB_???? NSA1 Come Away With Me_??? NSA2 Norah Jones_????????? NSA3 _????????????????????? NSA4 _????????????????????? NSA5 00:11 100%_????? NSA6 _????????????????????? NSA7_????????????????????? NSA8_?????????????????????

EVENT	PARAMETER	function	
NSE		Onscreen Display Information(mserver/iRadio) is Answered By the NSE Command.	
0		Display Line1 Information	NSE0*****_????? <cr></cr>
1		Display Line3 Information	NSE1 *****_????? <cr></cr>
2		Display Line4 Information	NSE2 *****_????? <cr></cr>
3		Display Line5 Information	NSE3 *****_????? <cr></cr>
4		Display Line6 Information	NSE4 *****_????? <cr></cr>
5		Display Line7 Information	NSE5 *****_????? <cr></cr>
6		Display Line8 Information	NSE6 *****_????? <cr></cr>
7		Display Line9 Information	NSE7*****_????? <cr></cr>
8		Display Line10 Information	NSE8*****_????? <cr> *:UTF-8 CODE Character(MAX95byte) :_Null ?: Don't Care (The character after Null should be disregarded) :Cursor&amp;Playable Music Information Data(1Byte) Bit1:Playable Music =1 Bit2,3:Don't Care Bit4:CURSOR SELECT=1 Bit5,6,7,8:Don't Care *****_?????:96byte Fixed </cr>
			<example> NSE0Now Playing USB_???? <cr> NSE1 Come Away With Me_???<cr> NSE2 Norah Jones_?????????<cr> NSE3 _?????????????????????<cr> NSE4 _?????????????????????<cr> NSE5 00:11 100%_??????<cr> NSE6 _?????????????????????<cr> NSE7_?????????????????????<cr> NSE8_?????????????????????<cr> </cr></cr></cr></cr></cr></cr></cr></cr></cr>

### iPod Extended Control

EVENT	PARAMETER	function	
IPA		Onscreen Display Information is Answered By the IPA Command.	
	0	Display Line1 Information	IPA0*****_??<CR>
	1	Display Line3 Information	IPA1 *****_??<CR>
	2	Display Line4 Information	IPA2 *****_??<CR>
	3	Display Line5 Information	IPA3 *****_??<CR>
	4	Display Line6 Information	IPA4 *****_??<CR>
	5	Display Line7 Information	IPA5 *****_??<CR>
	6	Display Line8 Information	IPA6 *****_??<CR>
	7	Display Line9 Information	IPA7 *****_??<CR>
	8	Display Line10 Information	IPA8#*****_??<CR>
	9	Display Line11 Information	IPA9*****_??<CR>  *:Character Length MAX96 _:Null ?:Exclusion(The character after Null should be disregarded) :Cursor Information Data(1Byte) Bit1:Playable Music=1 Bit2:Display Only=1 Bit3:Don't Care Bit4:CURSOR SELECT=1 Bit5-8:Don't Care #:Bit1-8:Don't Care

EVENT	PARAMETER	function	
IPA			<pre>&lt;example1-for ASD-1R&gt; IPA0Artist?????????????????&lt;CR&gt; IPA1 Ana Caram_?????????????&lt;CR&gt; IPA2 Badi Assad_?????????????&lt;CR&gt; IPA3 Christy Baron_?????????&lt;CR&gt; IPA4 Marta Gomez_?????????????&lt;CR&gt; IPA5 Rebecca Pidgeon_??????&lt;CR&gt; IPA6 Sara K_?????????????????&lt;CR&gt; IPA7 Valerie Joyce_?????????&lt;CR&gt; IPA8# SFL Songs RPT All_???&lt;CR&gt; IPA9 [ 2/ 6]_?????????&lt;CR&gt;  &lt;example2-for ASD-1R&gt; IPA0Now Playing iPod_??????&lt;CR&gt; IPA1 A HARD DAY'S NIGHT._??&lt;CR&gt; IPA2 /The Beatles_?????????&lt;CR&gt; IPA3 _?????????????????????????&lt;CR&gt; IPA4 A HARD DAY'S NIGHT_???&lt;CR&gt; IPA5 00:04_?????????????????&lt;CR&gt; IPA6 _?????????????????????????&lt;CR&gt; IPA7 _?????????????????????????&lt;CR&gt; IPA8# SFL Songs RPT All_???&lt;CR&gt; IPA9 _?????????????????????????&lt;CR&gt;</pre>

EVENT	PARAMETER	function	
IPE		Onscreen Display Information(iPOD) is Answered By the IPA Command.	
	0	Display Line1 Information	IPE0*****_???<CR>
	1	Display Line3 Information	IPE1 *****_???<CR>
	2	Display Line4 Information	IPE2 *****_???<CR>
	3	Display Line5 Information	IPE3 *****_???<CR>
	4	Display Line6 Information	IPE4 *****_???<CR>
	5	Display Line7 Information	IPE5 *****_???<CR>
	6	Display Line8 Information	IPE6 *****_???<CR>
	7	Display Line9 Information	IPE7 *****_???<CR>
	8	Display Line10 Information	IPE8#*****_???<CR>
	9	Display Line11 Information	IPE9*****_???<CR> * : <u>UTF-8 CODE Character (MAX95byte)</u> _ : Null ?: Exclusion (The character after Null should be disregarded) : Cursor Information Data (1Byte) Bit1: Playable Music=1 Bit2: Display Only=1 Bit3: Don't Care Bit4: CURSOR SELECT=1 Bit5-8: Don't Care # : Bit1-8: Don't Care  *****_????: 96byte Fixed

EVENT	PARAMETER	function	
IPE			<pre>&lt;example1-for ASD-1R&gt; IPE0Artist?????????????????&lt;CR&gt; IPE1 Ana Caram_?????????????&lt;CR&gt; IPE2 Badi Assad_?????????????&lt;CR&gt; IPE3 Christy Baron_?????????&lt;CR&gt; IPE4 Marta Gomez_?????????????&lt;CR&gt; IPE5 Rebecca Pidgeon_??????&lt;CR&gt; IPE6 Sara K_?????????????????&lt;CR&gt; IPE7 Valerie Joyce_?????????&lt;CR&gt; IPE8# SFL Songs RPT All_???&lt;CR&gt; IPE9 [ 2/ 6]_?????????&lt;CR&gt;  &lt;example2-for ASD-1R&gt; IPE0Now Playing iPod_??????&lt;CR&gt; IPE1 A HARD DAY'S NIGHT._??&lt;CR&gt; IPE2 /The Beatles_?????????&lt;CR&gt; IPE3 _?????????????????????????&lt;CR&gt; IPE4 A HARD DAY'S NIGHT_???&lt;CR&gt; IPE5 00:04_?????????????????&lt;CR&gt; IPE6 _?????????????????????????&lt;CR&gt; IPE7 _?????????????????????????&lt;CR&gt; IPE8# SFL Songs RPT All_???&lt;CR&gt; IPE9 _?????????????????????????&lt;CR&gt;</pre>

## Remote Lock/Panel Lock

EVENT	PARAMETER	function	example
SY	REMOTE LOCK ON	REMOTE CONTROL LOCK ON/OFF	SYREMOTE LOCK ON<CR>
	REMOTE LOCK OFF		SYREMOTE LOCK OFF<CR>
	PANEL LOCK ON	PANEL BUTTON(Except MASTER VOL.)CONTROL LOCK ON	SYPANEL LOCK ON<CR>
	PANEL+V LOCK ON	PANEL BUTTON & MASTER VOL. CONTROL LOCK ON	SYPANEL+V LOCK ON<CR>
	PANEL LOCK OFF	PANEL BUTTUM & MASTER VOL. CONTROL LOCK OFF	SYPANEL LOCK OFF<CR>

## UPGRADE ID Display

EVENT	PARAMETER	function	example
UG	IDN *****	ID Number for UPGRADE is displayed on FL Display *****:12-digit ID Number	UGIDN *****<CR>
	IDN NG		UGIDN NG<CR>