

HDA-1600 | LOW-Z/70 VOLT AMPLIFIER



Low-Z/70 Volt Amplifier



OVERVIEW

Perfect for commercial or residential applications, the HDA-1600 Low-Z/70 Volt Amplifier delivers 600 Watts of power per channel and features 4 unbalanced analog inputs and 1 balanced analog input. Two microphone inputs support phantom power and the amplifier supports ducking to automatically lower the volume of music playing for paging applications and microphone use.

HIGHLIGHTS

- 600 Watts / channel @ 8Ω; 1200 Watts / channel @ 4Ω / 2 x 600 Watts @ 70 Volt
- 96 kHz / 24-bit streaming high-definition audio quality
- Each zone supports a full 5-band parametric EQ
- Audio ducking capability
- Page event support
- Store up to 10 .WAV Files in each amplifier (for doorbell ring chime and/or trigger alert chimes)
- Inputs:
 - 4 Unbalanced Analog Audio Inputs
 - 1 Balanced Analog Audio Input
 - 2 Microphone Inputs with URC DSP features (supporting phantom power)
- Outputs:
 - 1 stereo amplifier output channel / 2 independent mono output channels

*HDA-SW5 AVB Network Switch is needed when more than 1 HDA product is installed

SPECIFICATIONS

SKU

HDA-1600-70V, UPC 656787-503021

System

Total Control®

Advanced system controller and professional programming required

In the Box

HDA-1600-70V, Ethernet Cable, Power Cord, Rack Mount Ears

Dimensions

434.98 mm (17.125") W x 98.425mm (3.875") H x 303.2mm (11.94") D

Weight

5.55kg (12.25 lbs)

Warranty

2 year limited warranty

✉ totalcontrol@urc-automation.com

🌐 www.urc-automation.com

