

HDA-4100 | MULTI-ZONE AMPLIFIER



4 Source, 4 Zone (stereo) or 8 Zone (mono) Multi-Zone Amplifier



OVERVIEW

Perfect for smaller installations, the HDA-4100 multi-zone amplifier delivers 100 Watts of power to 4 stereo channels or 8 single channel mono zones.

HIGHLIGHTS

- 100 Watts / channel @ 8Ω; 200 Watts / channel @ 4Ω
- 96 kHz / 24-bit streaming high-definition audio quality
- High pass & low pass filters per zone
- Each zone supports a full 5-band parametric EQ
- Audio ducking capability
- Page event support
- Store up to 10 .WAV Files in each amplifier (for doorbell ring chime and/or trigger alert chimes)
- Permanent zone grouping (also between multiple amplifiers)
- Inputs:
 - 4 RCA analog inputs
- Outputs:
 - 4 stereo amplifier output channels / 8 mono output channels
 - 2 assignable pre-amp outputs
- High pass & low pass filters per zone
- Two 12 Volt triggers
- Gigabit Ethernet Connection (Full Duplex, for Gigabit LAN only)

*HDA-SW5 AVB Network Switch is needed when more than 1 HDA product is installed

SPECIFICATIONS

SKU

HDA-4100, UPC 656787-503014

System

Total Control®

Advanced system controller and professional programming required

In the Box

HDA-4100, Ethernet Cable, Power Cord, Rack Mount Ears

Dimensions

434.98 mm (17.125") W x 98.425mm (3.875") H x 303.2mm (11.94") D

Weight

5.39 kg (11.9lbs)

Warranty

2 year limited warranty

✉ totalcontrol@urc-automation.com

🌐 www.urc-automation.com

